Flashing Siren

Dual Way Communication

MD-334R

- Double flashing light.
- Built-in tweeter.
- 2-way communication with alarm control panel.
- Can arm/disarm by remote controller.
- with tamper alarm.
- Can enroll 16wireless devices.

MD-334R is a kind of alarm device with strong popularity. Its power from the adapter or external lithium batteries via wireless signal. Its communicate with alarm panel, detector, remote etc. Which work with the same frequency as the siren and achieve flash light and alarm sound when alarm occurs. And it also give prompt sound when the remote which have code with the siren to arm or disarm. This siren has anti-temper function to avoid intentional damage or dismantle. When alarm happens it make high alarm sound. Commonly used in the outdoor of the house, office, factory, shops etc.

Specification

Overview	
Wireless communication distance	100m （In the open area）
Working voltage	DC12~15V
backup power	7.4V/1000mAh(Rechargeable lithium battery)
Quiescent Current	＜15mA
Working current	＜1.2A
Debugging method	ASK
Working frequency	433/868MHz(Optional)

Alarm loudness	about 100dB
Sirens ringing time	150 seconds
Size	(L*W*H)230*165*55mm
Trigger mode	When arm by remote, the detector and magnetic contact etc. which have coded with the siren will alarm when they are triggered.Or the panel send signal to the siren,and it makes alarm. It can code with Max 16 wireless Device.