Detector
Series

SR01-ZB

When used with a smart host or gateway, when the smart door sensor and other sensor devices are illegally triggered, the sound and light siren will emit a 110dB high-decibel alarm sound, accompanied by flashing lights, which has a great shock effect on illegal intruders.

Specification

Overview			
Status display	LED light display	Working mode	AC90V—240V
Ultra-low power consumption	Long battery standby	Working current	≤40uA monitoring, ≤200mA alarm
Alarm content	Anti-dismantling, low voltage	Working environment	-10°C~50°C, <95%RH
Wireless networking	Zigbee IEEE802.15.4	Dimensions	φ80*70mm
Alarm sound	≥110dB		